

CMOS 4-bit 1 Chip Microcomputer

EPROM equipped

Description


The CXP50100 is a CMOS 4-bit microcomputer common with piggyback / evaluation chip which are developed for CXP50112/CXP50116 function evaluation.

Features

- Instruction cycle 1.9 μ s / 4.19MHz
122 μ s / 32kHz
(Selectable at programming)
- ROM capacity Maximum 32k bytes
(EPROM LCC type 27C256 equipped)
- RAM capacity 544 \times 4 bits
(Display area included)
- 51 general purpose I/O ports
- 8 large current ports (Ports C, D)
- Fluorescent display panel controller/driver
(Maximum 256 segments display possible)
 - 1 to 16 digits dynamic scan display
(1 to 8 digits at 24 segments)
 - Page mode/variable mode
 - Dimmer function
 - High withstand voltage output (40V)
 - Pull-down resistance
(Mask option for each bit)
- 14-bit PWM output for D/A conversion
- Remote control receive circuit
(Be independent of the timer/counter)
- 3-bit A/D converter (8 channels per circuit)
- 32kHz reload timer/event counter
- Power supply voltage detection reset function
- Rich wake up functions
 - WP pin
 - 4 general purpose ports (Edge detection)
 - Remote control receive circuit
 - 32kHz timer/counter
- 8-bit / 4-bit variable serial I/O with prescaler
- 8-bit timer with prescaler, 8-bit timer/event counter with prescaler, 18-bit time base timer and 8-bit reload timer with prescaler, independently controlled

Package Outline

Unit : mm




- Arithmetic and logical operations possible between the entire ROM area, I/O area and the accumulator by means of memory mapped I/O
- Reference to the entire ROM area is possible with the table look-up instruction
- 2 kinds of power down modes of sleep and stop
- Power on reset circuit (Mask option)
- Provided with 80-pin ceramic QFP

Note) The mask option is fixed according to a kind of CXP50100.
See the list of products for details.


Structure

Silicon gate CMOS IC

Block Diagram











Pin Configuration (Top View)






Note) 1. Do not make any connections to NC pins.
2. Use 27C256 type for EPROM.

Pin Description

Symbol	Name	I/O	Equivalent Circuit	Description
V _{DD}	Supply voltage	—		Positive voltage supply pin
V _{SS}	Grounding voltage	—		GND pin
EXTAL	Clock input	I		Clock oscillation circuit input pin. Connect the crystal oscillator or ceramic resonator between the EXTAL and XTAL. To use an external clock input, connect the clock oscillation source to the EXTAL pin and open the XTAL pin.
XTAL	Clock output	O		Clock oscillation circuit output pin
RST	Reset	I/O		Serves as the incorporated power-on reset circuit output pin. When inputting a reset signal from the outside, provide 2 instruction cycles or longer of an "L" level (0V).
INT	External interrupt	I		Serves as interrupt input pin. Permits the selection with a program of the edge and the level modes.
EC	Event counter input	I		Event counter input pin.
SI/PX2	Serial input Port X	I		Doubles as a serial interface (8 bits) input pin and as bit "2" (input) of port X.
SO/PX1	Serial output Port X	I/O		Doubles as a serial interface (8 bits) output pin and as bit "1" (input) of port X.
SC/PX0	Serial clock Port X	I/O		Doubles as clock input/output pin for the serial interface and as bit "0" (input) of port X.

Symbol	Name	I/O	Equivalent Circuit	Description
RMC/ PY3	Remote control input Port Y	I		Remote control receive circuit input pin. Input pin for bit "3" of port Y.
WP/PY2	Wake-up input Port Y	I	Schmitt inverter input	Doubles as a wake-up input pin to release the standby state, and as bit "2" (input) of port Y.
PWM/ PY1	PWM output Port Y	O		Doubles as a PWM generator (14 bits) output and as bit "1" (output) of port Y.
PY0	Port Y	O	(When reset : 1) Inverter output	Output pin for bit "0" of port Y.
PA0 to PA3	Port A	I/O		This 4-bit input/output port permits its each individual port to be programmed to serve for input or output. Its output format is a tri-state or pull-up resistor output.
PB0/AD4 to PB3/AD7	Analog input Port B	I/O	B and I only for A/D input port	 This 4-bit input/output port permits its each individual bit to be programmed to serve either as input or output. Its output format is a tri-state or pull-up resistor output. It is also used for A/D converter input.
PC0 to PC3	Port C	I/O		This 4-bit input/output port permits its each individual port to be programmed to serve for input or output. Its output format is a tri-state or pull-up resistor output.
PD0 to PD3	Port D	I/O		This 4-bit input/output port has the functions that are equivalent to those of port C.
PE0 to PE3	Port E	I/O		This 4-bit input/output port has the functions that are equivalent to those of port C.
PF0 to PF3	Port F	I/O		This 4-bit input/output port has the functions that are equivalent to those of port C.
PI0/AD0 to PI3/AD3	Analog input Port I	I/O		This 4-bit input/output port has the functions that are equivalent to those of port C. It is also used for A/D converter input.

Symbol	Name	I/O	Equivalent Circuit	Description
V _{FDP}	Power supply for FDP	-		Load current supply pin needed when load resistance is built-in to output driver for FDP (Fluorescent display pannel).
T0 to T7	Timing	O		Lower 8-digit output pin of the FDP timing signal.
T8/S23 to T15/S16	Timing/segment	O		Combination output pin of higher 8-digit of the FDP timing signal and the segment signal.
PG0/S4 to PG3/S7	Port G/segment	O		Combination pin of the 4-bit output port and FDP segment signal output.
PH0/S0 to PH3/S3	Port H/segment	O		The same as port G.
PJ0/S12 to PJ3/S15	Port J/segment	O		The same as port G.
PK0/S8 to PK3/S11	Port K/segment	O		The same as port G.
TEX	32kHz T/C clock input	I		Input pin of the 32kHz timer clock generated circuit. Connect 32,768 kHz crystal oscillator between TEX and TX. Connect clock oscillation source to TEX pin and bleed TX pin when this circuit is used as event clock input.
TX	32kHz T/C clock output	O		Output pin of the clock generated circuit.
V _{REF}	Reference voltage input	I		Reference voltage input for power supply voltage resetting circuit. Connect the zener diode normally.

Absolute Maximum Ratings

Ta = -20°C to +75°C, Vss = 0V

Item	Symbol	Rating	Unit	Remarks
Power supply voltage	VDD	-0.3 to +7.0	V	
Input voltage	VIN	-0.3 to +7.0*¹	V	
Output voltage	VOUT	-0.3 to +7.0*¹	V	
Display output voltage	VOD	VDD - 40 to VDD + 0.3	V	As P channel transistor is open drain, VDD voltage is determined as standard.
High level output current	IOH	-5	mA	Other than display output pins*² : per pin
	IODH1	-15	mA	Display output S0 to S15 : per pin
	IODH2	-35	mA	Display output T0 to T7, T8/S23 to T15/S16 : per pin
High level total output current	Σ IOH	-40	mA	Total of other than display output pins
	Σ IODH	-100	mA	Total of display output pins
Low level output current	IOL	15	mA	Port 1 pin
	IOLC	20	mA	High current port pin*³
Low level total output current	Σ IOL	100	mA	Entire pin total
Operating temperature	Topr	-20 to +75	°C	
Storage temperature	Tstg	-55 to +150	°C	
Allowable power dissipation*⁴	Pd	600	mW	QFP

Note) Usage exceeding absolute maximum ratings may permanently impair the LSI. Normal operation should better take place under the recommended operation conditions. Exceeding those conditions may adversely affect the reliability of the LSI.

*¹) VIN and VOUT should not exceed VDD + 0.3V.

*²) Specifies the output current of the general purpose I/O port PA to PF, PI, SO, SC, PY0 and PY1.

*³) The high current operation transistors are the N-CH transistors of the PC and PD ports.

*⁴) Allowable power dissipation of EPROM excluded.

Recommended Operating Condition

Vss = 0V

Item	Symbol	Min.	Max.	Unit	Remarks
Power supply voltage	VDD	4.5	5.5	V	Guaranteed range of operation by EXTAL colck
		2.5	5.5	V	Guaranteed range of operation by TEX colck, guaranteed range of data hold during STOP
High level input voltage	VIH	0.7VDD	VDD	V	
	VIHS	0.8VDD	VDD	V	Hysteresis input*¹
	VIHEX	VDD - 0.4	VDD + 0.3	V	EXTAL pin*²
Low level input voltage	VIL	0	0.3VDD	V	
	VILS	0	0.2VDD	V	Hysteresis input*¹
	VILEX	-0.3	0.4	V	EXTAL pin*²
Operating temperature	Topr	-20	+75	°C	

*¹) The TEX pin when the counter mode is selected by each of INT, EC, PX0, PX2, PY2, PY3, RST pins and mask option.

*²) Specified only during external clock input.

Electrical Characteristics**DC characteristics**Ta = -20°C to +75°C, V_{SS} = 0V

Item	Symbol	Pin	Conditions	Min.	Typ.	Max.	Unit
High level output voltage	V _{OH}	PA to PF, PI PX0, PX1 PY0, PY1 RST (V _{OL} only)	V _{DD} = 4.5V, I _{OH} = -0.5mA	4.0			V
			V _{DD} = 4.5V, I _{OH} = -1.0mA	3.5			V
Low level output voltage	V _{OL}	PC, PD	V _{DD} = 4.5V, I _{OL} = 1.8mA			0.4	V
			V _{DD} = 4.5V, I _{OL} = 3.6mA			0.6	V
Input current	I _{IHE}	EXTAL	V _{DD} = 5.5V, V _{IH} = 5.5V	0.5		40	μA
	I _{ILE}		V _{DD} = 5.5V, V _{IL} = 0.4V	-0.5		-40	μA
	I _{IHT}	TEX* ³	V _{DD} = 5.5V, V _{IH} = 5.5V	0.1		10	μA
	I _{ILT}		V _{DD} = 5.5V, V _{IL} = 0.4V	-0.1		-10	μA
	I _{ILR}	RST * ²		-1.5		-400	μA
High impedance I/O leakage current	I _{Iz}	PA to PF, PI PX0 to PX2, PY2, PY3, EC, INT, RST * ² , TEX* ³	V _{DD} = 5.5V V _I = 0, 5.5V			± 10	μA
Display output current	I _{OH}	S0 to S15	V _{DD} = 4.5V V _{OH} = V _{DD} - 2.5V	-7			mA
		S16/T15 to S23 /T8, T0 to T7		-18			mA
Open drain output leakage current (P-CH Tr OFF in state)	I _{OL}	S0 to S15, S16/ T15 to S23/T8, T0 to T7	V _{DD} = 5.5V V _{OL} = V _{DD} - 35V			-20	μA
Pull-down resistance* ¹	R _L	S0 to S15, S16/ T15 to S23/T8, T0 to T7	V _{DD} = 5V V _{FDP} = V _{DD} - 35V	60	100	270	kΩ
Supply current* ⁴	I _{DD1}	V _{DD}	Entire output pins open				
	I _{DD2}		Crystal oscillation (C1 = C2 = 22pF) of V _{DD} = 5.5V, 4.19MHz		7	20	mA
	I _{DDSP1}		Crystal oscillation (C1 = C2 = 18pF) of V _{DD} = 3V, 32kHz		50	250	μA
	I _{DDSP2}		SLEEP mode				
	I _{DPS1}		V _{DD} = 5.5V, 4.19MHz oscillation		5	12	mA
	I _{DPS2}		V _{DD} = 3V, 32kHz oscillation		40	200	μA
			STOP mode				
Input capacity	C _{IN}	PA to PF, PI, PX, PY2, PY3, EXTAL, TEX, EC, INT, RST	V _{DD} = 3V, 32kHz with T/C		7	40	μA
			V _{DD} = 5.5V, 32kHz without T/C (For mask option select counter, Pin is fixed.)			10	μA
			Clock 1MHz 0V other than the measured pins		10	20	pF

- *1) In case the incorporated pull-down resistance has been selected with mask option.
- *2) \overline{RST} pin specifies the input current when the pull-up resistance is selected, and specifies leakage current when nonresistance is selected.
- *3) The TEX pin specifies the input current when the 32kHz oscillation is selected by the mask option, and specifies the leak current when the counter mode is specified.
- *4) Power supply current of EPROM excluded.

AC Characteristics

(1) Clock timing

$T_a = -20^\circ\text{C}$ to $+75^\circ\text{C}$, $V_{DD} = 4.5\text{V}$ to 5.5V , $V_{SS} = 0\text{V}$

Item	Symbol	Pin	Conditions	Min.	Typ.	Max.	Unit
System clock frequency	f_c	XTAL EXTAL	Fig. 1, Fig. 2	1		5	MHz
System clock input pulse width	t_{XL} t_{XH}	EXTAL	Fig. 1, Fig. 2 (External clock drive)	90			ns
System clock input rising and falling times	t_{CR} t_{CF}	TEX* ² TX				200	ns
System clock frequency	f_{CS}	TEX* ² TX	$V_{DD} = 2.5$ to 5.5V Fig. 2		32.768		kHz
Event count clock input pulse width	t_{EL} t_{EH}	\overline{EC}	Fig. 3	t_{sys}^{*1} +0.05			μs
Event count clock input rising and falling times	t_{ER} t_{EF}	\overline{EC}	Fig. 3			20	ms
Event count input clock input pulse width	t_{TL} t_{TH}	TEX* ³	Fig. 3	10			μs
Event count input clock rising and falling times	t_{TR} t_{TF}	TEX* ³	Fig. 3			20	ms

*1) t_{sys} in the EXTAL input clock is $t_{sys} = 8/f_c$

t_{sys} in the TEX input clock is $t_{sys} = 4/f_{CS}$

*2) Specified when the crystal oscillation mode is selected by the mask option.

*3) Specified when the counter mode is selected by the mask option.

Note) When adjusting the frequency accurately, there may be cases in which they may differ from Fig. 2.




Fig. 1 Clock timing




Fig. 2 Clock applying condition




Fig. 3 Event count clock timing

(2) Serial transfer

 $T_a = -20^\circ\text{C} \text{ to } +75^\circ\text{C}$, $V_{DD} = 4.5\text{V} \text{ to } 5.5\text{V}$, $V_{SS} = 0\text{V}$

Item	Symbol	Pin	Conditions	Min.	Max.	Unit
Serial transfer clock ($\overline{\text{SC}}$) cycle time	tkcy	$\overline{\text{SC}}$	Input mode	$t_{\text{sys}}/4 + 1.42$		μs
			Output mode	t_{SIO}		μs
Serial transfer clock ($\overline{\text{SC}}$) high and low level widths	tkh tkl	$\overline{\text{SC}}$	Input mode	$t_{\text{sys}}/8 + 0.7$		μs
			Output mode	$t_{\text{SIO}}/2 - 0.1$		μs
Serial data input setup time (against $\overline{\text{SC}} \uparrow$)	tsik	SI	$\overline{\text{SC}}$ input mode	0.1		μs
			$\overline{\text{SC}}$ output mode	0.2		μs
Serial data input hold time (against $\overline{\text{SC}} \uparrow$)	tksi	SI	$\overline{\text{SC}}$ input mode	$t_{\text{sys}}/8 + 0.5$		μs
			$\overline{\text{SC}}$ output mode	0.1		μs
Data delay time from $\overline{\text{SC}}$ falling	tkso	SO			$t_{\text{sys}}/8 + 0.5$	μs

Note 1) t_{sys} is the EXTAL input clock $t_{\text{sys}} = 8/\text{fc}$

(It cannot be used with TEX input clock)

tsio is turned into either $2t_{\text{sys}}$, $4t_{\text{sys}}$ or $16t_{\text{sys}}$ by means of a program2) The Load of data output delay is $50\text{pF} + 1\text{TTL}$




Fig. 4 Serial transfer timing

(3) A/D converter

 $T_a = -20^\circ\text{C} \text{ to } +75^\circ\text{C}, V_{ss} = 0\text{V}$

Analog input voltage	Pin	Conditions	Digital conversion value
0.0 to 0.33V	AD0 to AD7	$V_{DD} = 5\text{V}$	000
0.82 to 1.29V			001
1.78 to 2.21V			010
2.69 to 3.06V			011
3.56 to 4.06V			100
4.62 to 5.0V			101

Note) The digital conversion value are the values when FF_H address of the RAM file 1 in the program are read.

(4) Power Supply Voltage Detection Reset Function

 $T_a = -20^\circ\text{C} \text{ to } +75^\circ\text{C}$, $V_{ss} = 0\text{V}$

Item	Symbol	Pin	Conditions	Min.	Typ.	Max.	Unit
Power supply voltage detection reset function of operation voltage range	V_{LPOP}	V_{DD}	Voltage range allowing system operation	2.5		5.5	V
Power supply voltage drop detection function	V_{POP}	V_{DD}	When V_{REF} pin voltage is 3.3V Flag set when voltage drops System reset when voltage rises	3.8	4.0	4.2	V

The graph in Fig. 5 shows the relationship between the power supply voltage V_{DD} and reference voltage V_{REF} of the power supply voltage detection reset function.

Note) The graph in Fig. 5 serves as guide to the function operation area obtained using average devices.
Individual adjustment is needed when Zener diodes, etc., are connected to the V_{REF} pin.




Fig. 5 Power supply voltage detection reset function chart

(5) Others

 $T_a = -20^\circ\text{C} \text{ to } +75^\circ\text{C}$, $V_{DD} = 4.5\text{V} \text{ to } 5.5\text{V}$, $V_{ss} = 0\text{V}$

Item	Symbol	Pin	Conditions	Min.	Max.	Unit
External interruption high and low level widths	t_{I1H}, t_{I1L}	INT	During edge detection mode	$t_{sys} + 0.05$		μs
Reset input low level width	t_{RSL}	RST		$2t_{sys}^*$		μs
Wake-up input high level width	t_{WPB}	WP	STOP mode	500		ns
			SLEEP mode	$t_{sys} + 0.05$		μs
Wake-up input high and low level widths	t_{WPB} t_{WPAL}	PA0 to PA3	STOP mode	500		ns
			SLEEP mode	500		ns

Note) t_{sys} in the EXTAL input clock is $8/f_c$

*1) For resetting when operating in TEX input clock, hold the low level more than the oscillation stabilizing time of EXTAL input clock.




Fig. 6 Interruption input timing




Fig. 7 Reset input timing




Fig. 8 Wake-up input timing





Fig. 9 Wake-up input timing

Power on reset * $T_a = -20^{\circ}\text{C}$ to $+75^{\circ}\text{C}$, $V_{ss} = 0\text{V}$

Item	Symbol	Pin	Conditions	Min.	Max.	Unit
Power supply rising time	t_R	V_{DD}	Power on reset	0.05	50	ms
Power supply cut-off time	t_{OFF}		Repetitive power on reset	1		ms

* Specifies only when power on reset function is selected.



The power supply should rise smoothly.

Fig. 10 Power on reset

Notes on Application

See Fig. 11, Additive capacity calculation chart, when using the crystal oscillator and select the appropriate capacity.




Fig. 11 Crystal oscillation circuit additive capacity calculation chart

Note) The above chart shows a range in which the average quartz resonator has a relatively fast oscillation rising edge and stable characteristics. The capacity should be selected to correspond to the appropriate constant for each quartz resonator, should the frequency of the quartz resonator be accurately adjusted.

Fig. 12 shows recommended circuits and oscillators.


Use the trimmer capacitor to C1, in the case of accurate adjustment of the oscillation frequency.

1. Main clock

4.19MHz

Ceramic resonator


Manufacturer	Model	Frequency range(MHz)	C1(pF)	C2(pF)	Rd(Ω)
MURATA MFG CO., LTD.	CSA4.19MG040	4.19	100	100	—
	CSA4.19MGW040		built in	built in	—



Crystal oscillator

Manufacturer	Model	Frequency range(MHz)	C1(pF)	C2(pF)	Rd(Ω)
CITIZEN WATCH CO., LTD.	CSA309	4.19	10 (20 trimmer)	10	—
	AT-51		15 (20 trimmer)	15	6.8k
	HC-49/U-S		22 (20 trimmer)	22	3.3k

2. 32kHz Timer/Counter



Manufacturer	Model	Frequency range(kHz)	C1(pF)	C2(pF)	Rd(Ω)
CITIZEN WATCH CO., LTD.	CFS-308	32.768	18 (20 trimmer)	18	—
	MX-38T		22 (20 trimmer)	22	470k
	P3		22 (20 trimmer)	22	3.3k

About the details of oscillators, please inquire the makers or the agencies.

Fig. 12 Recommended oscillation circuit

When using the A/D converter as the key input, it is recommended that the circuit structure shown in Fig. 13 be used.






Fig. 13 Recommended example of key circuit by A/D converter

EPROM Read TimingReference : $T_a = -20$ to $+75$ °C, $V_{DD} = 4.5$ to $5.5V$, $V_{SS} = 0V$

Item	Symbol	Pin	Min.	Max.	Unit
Address→Data Input delay time	t_{ACC}	A0 to A14 I0 to I7		300	ns
Address→Data Retention time	t_{IH}	A0 to A14 I0 to I7	0		ns

EPROM Timing

Conduct as follows for the switchover of piggy mode/evaluation mode.

**List of products**

Option item	Product	CXP50100-U01Q
Package	80 pins plastic QFP	80 pins ceramic QFP
ROM capacity	12k bytes/16k bytes	EPROM 32k bytes
Pull-up resistance of reset pin	Mask/Non-mask	Mask
Power on reset circuit	Mask/Non-mask	Mask
32kHz timer/counter	Timer/counter	Timer mode
High withstand voltage pull-down resistance	Mask/Non-mask	Non-mask

Note) Chip for both piggy and evaluation.

О компании

ООО "ТрейдЭлектроникс" - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Наличие собственной эффективной системы логистики обеспечивает надежную поставку продукции по конкурентным ценам в точно указанные сроки.

Срок поставки со стоков в **Европе и Америке – от 3 до 14 дней.**

Срок поставки из **Азии – от 10 дней.**

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Предоставляем спец цены на элементы для создания инженерных сэмплов.

Упорный труд, качественный результат дают нам право быть уверенными в себе и надежными для наших клиентов.

Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование

Наша организация особенно сильна в поставках модулей, микросхем, пассивных компонентов, ксайленсах (ХС), EPF, EPM и силовой электроники.

Большой выбор предлагаемой продукции, различные виды оплаты и доставки, позволят Вам сэкономить время и получить максимум выгоды от сотрудничества с нами!

Перечень производителей, продукцию которых мы поставляем на российский рынок

AMD

ANALOG DEVICES

BOURNS

Coilcraft
The world's largest manufacturer of magnetic components

élan tec
Semiconductor, Inc.

HARRIS

infineon

JRC

MICREL
Innovation through Technology™

MOTOROLA

nichicon

PHILIPS

Excellence in Electronics
ROHM

ST SGS-THOMSON
MICROELECTRONICS

Sipex

TAIYO YUDEN

TOKO

ZILAS

Winbond
Electronics Corp.

Allegro
MicroSystems, Inc.

ATMEL

BURR - BROWN
BB

EXAR

HITACHI
Inspire the Next

intel

Lattice
Semiconductor Corporation

muRata
Leader in Electronics

OKI

QUALCOMM

SAMSUNG

SHARP

SONY

TDK

TOSHIBA

XORX

ALTERA

AVX
Ceramic

CATALYST

CYPRESS
SEMICONDUCTOR

FAIRCHILD
SEMICONDUCTOR

HOLTEK

International IOR Rectifier

LINEAR TECHNOLOGY
MITSUBISHI

National Semiconductor

ON Semiconductor
UN

REALTEK
Ralink Semiconductor Corp.

SANYO

SHINDENGEN

SS

TECCOR
ELECTRONICS

TUNDRA

XILINX

Amphenol

Bay Linear

CIRRUS LOGIC

DALLAS

FUJITSU

IDT

intersil

MAXIM

molex

NEC

Panasonic

RENESAS

SII
SII Instruments Inc.

SIEMENS

ST

TEXAS INSTRUMENTS

VISHAY

ZETEX
SEMICONDUCTORS



гарантия бесперебойности производства и
качества выпускаемой продукции

С удовольствием будем прорабатывать для Вас поставки всех необходимых компонентов по текущим запросам для скорейшего выявления групп элементов, по которым сотрудничество именно с нашей компанией будет для Вас максимально выгодным!

С уважением,

Менеджер отдела продаж ООО

«Трейд Электроникс»

Шишлаков Евгений

8 (495)668-30-28 доб 169

manager28@tradeelectronics.ru

<http://www.tradeelectronics.ru/>