CS52845

Current Mode PWM Control Circuit with 50% Max Duty Cycle

Description

The CS52845 provides all the necessary features to implement off-line fixed frequency current-mode control with a minimum number of external components.

The CS52845 incorporates a new precision temperature-controlled oscillator to minimize variations in frequency. An internal toggle flip-flop, which blanks the output every other clock cycle, limits the duty-cycle range to less than 50%.


An undervoltage lockout ensures that V_{REF} is stabilized before the output stage is enabled. In the CS52845 turn on is at 8.4V and turn off at 7.6V.

Other features include low start-up current, pulse-by-pulse current limiting, and a high-current totem pole output for driving capacitive loads, such as gate of a power MOSFET. The output is low in the off state, consistent with N-channel devices.

Absolute Maximum Ratings

Supply Voltage (I_{CC}<30mA) .....Self Limiting
Supply Voltage (Low Impedance Source) 30V
Output Current .....±1A
Output Energy (Capacitive Load) 5μJ
Analog Inputs (V_{FB}, V_{SENSE}) .....-0.3V to 5.5V
Error Amp Output Sink Current 10mA
Lead Temperature Soldering
Reflow (SMD styles only) .....60 sec. max above 183°C, 230°C peak

Block Diagram




Features


- Optimized for Off-line Control
- Temperature Compensated Oscillator
- 50% Maximum Duty-cycle Clamp
- V_{REF} Stabilized before Output Stage is Enabled
- Low Start-up Current
- Pulse-by-pulse Current Limiting
- Improved Undervoltage Lockout
- Double Pulse Suppression
- 1% Trimmed Bandgap Reference
- High Current Totem Pole Output

Package Options

8L SO Narrow



14L SO Narrow



Cherry Semiconductor
Cherry Semiconductor Corporation
2000 South County Trail, East Greenwich, RI 02818
Tel: (401)885-3600 Fax: (401)885-5786
Email: info@cherry-semi.com
Web Site: www.cherry-semi.com

Electrical Characteristics: $-40 \le T_A \le 85°C$; V_{CC} = 15V (Note 1); R_T = 10kΩ; C_T = 3.3nF for sawtooth mode.unless otherwise stated.

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
■ Reference Section					
Output Voltage	T_J=25°C, I_{REF}=1mA	4.95	5.00	5.05	V
Line Regulation	$12 \le V_{CC} \le 25V$		6	20	mV
Load Regulation	$1 \le I_{REF} \le 20mA$		6	25	mV
Temperature Stability	(Note 2)		0.2	0.4	mV/°C
Total Output Variation	Line, Load, Temp. (Note 2)	4.90		5.10	V
Output Noise Voltage	$10Hz \le f \le 10kHz$, T_J=25°C (Note 2)		50		μV
Long Term Stability	T_A=125°C, 1000 Hrs. (Note 2)		5	25	mV
Output Short Circuit	T_A=25°C	-30	-100	-180	mA
■ Oscillator Section					
Initial Accuracy	Sawtooth Mode, T_J=25°C	47	52	57	kHz
Voltage Stability	$12 \le V_{CC} \le 25V$		0.2	1.0	%
Temperature Stability	Sawtooth Mode $T_{MIN} \le T_A \le T_{MAX}$ (Note 2)		5		%
Amplitude	V_{OSC} (peak to peak)		1.7		V
■ Error Amp Section					
Input Voltage	V_{COMP}=2.5V	2.45	2.50	2.55	V
Input Bias Current	V_{FB}=0V		-0.3	-1.0	μA
A_{VOL}	$2 \le V_{OUT} \le 4V$	65	90		dB
Unity Gain Bandwidth	(Note 2)	0.7	1.0		MHz
PSRR	$12 \le V_{CC} \le 25V$	60	70		dB
Output Sink Current	V_{FB}=2.7V, V_{COMP}=1.1V	2	6		mA
Output Source Current	V_{FB}=2.3V, V_{COMP}=5V	-0.5	-0.8		mA
V_{OUT} HIGH	V_{FB}=2.3V, R_L=15kΩ to Gnd	5	6		V
V_{OUT} LOW	V_{FB}=2.7V, R_L=15kΩ to V_{REF}		0.7	1.1	V
■ Current Sense Section					
Gain	(Notes 3 & 4)	2.85	3.00	3.15	V/V
Maximum Input Signal	V_{COMP}=5V (Note 3)	0.9	1.0	1.1	V
PSRR	$12 \le V_{CC} \le 25V$ (Note 3)		70		dB
Input Bias Current	V_{Sense}=0V		-2	-10	μA
Delay to Output	T_J=25°C (Note 2)		150	300	ns
■ Output Section					
Output Low Level	I_{SINK}=20mA		0.1	0.4	V
I_{SINK}=200mA			1.5	2.2	V
Output High Level	I_{SOURCE}=20mA	13.0	13.5		V
	I_{SOURCE}=200mA	12.0	13.5		V
Rise Time	T_J=25°C, C_L=1nF (Note 2)		50	150	ns
Fall Time	T_J=25°C, C_L=1nF (Note 2)		50	150	ns

Electrical Characteristics: Unless otherwise stated, specifications apply for -40 ≤ T_A ≤ 85°C; V_{CC} = 15V (Note 1); R_T = 10kΩ; C_T = 3.3nF for sawtooth mode.

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
■ Total Standby Current					
Start-Up Current			0.5	1.0	mA
Operating Supply Current	V_{FB}=V_{Sense}=0V R_T=10kΩ, C_T=3.3nF		11	17	mA
V_{CC} Zener Voltage	I_{CC}=25mA		34		V
■ PWM Section					
Maximum Duty Cycle		46	48	50	%
Minimum Duty Cycle		0			%
■ Undervoltage Lockout Section					
Start Threshold		7.8	8.4	9.0	V
Min. Operating Voltage	After Turn On	7.0	7.6	8.2	V

Notes: 1. Adjust V_{CC} above the start threshold before setting at 15V.

2.These parameters, although guaranteed, are not 100% tested in production.


3. Parameter measured at trip point of latch with V_{FB}=0.

4. Gain defined as: $A = \frac{\Delta V_{COMP}}{\Delta V_{Sense}}$; $0 \le V_{Sense} \le 0.8V$.

Package Pin Description

PACKAGE PIN #		PIN SYMBOL	FUNCTION
8L SO Narrow	**14L SO Narrow**		
1	1	COMP	Error amp output, used to compensate error amplifier.
2	3	V_{FB}	Error amp inverting input.
3	5	Sense	Noninverting input to Current Sense Comparator.
4	7	OSC	Oscillator timing network with Capacitor to Ground, resistor to V_{REF}.
5	9	Gnd	Ground.
5	8	Pwr Gnd	Output driver Ground.
6	10	V_{OUT}	Output drive pin.
7	11	V_{CC}Pwr	Output driver positive supply.
7	12	V_{CC}	Positive power supply.
8	14	V_{REF}	Output of 5V internal reference.
	2,4,6,13	NC	No Connection.

Test Circuit Open Loop Laboratory Test Fixture



Circuit Description




Figure 1: Startup voltage for the CS52845.

Undervoltage Lockout

During Undervoltage Lockout (Figure 1), the output driver is biased to sink minor amounts of current. The output should be shunted to ground with a resistor to prevent activating the power switch with extraneous leakage currents.

PWM Waveform

To generate the PWM waveform, the control voltage from the error amplifier is compared to a current sense signal which represents the peak output inductor current (Figure 2). An increase in V_{CC} causes the inductor current slope to increase, thus reducing the duty cycle. This is an inherent feed-forward characteristic of current mode control, since the control voltage does not have to change during changes of input supply voltage.

When the power supply sees a sudden large output current increase, the control voltage will increase allowing the duty cycle to momentarily increase. Since the duty cycle tends to exceed the maximum allowed to prevent transformer saturation in some power supplies, the internal oscillator waveform provides the maximum duty cycle clamp as programmed by the selection of OSC components.




Figure 2: Timing Diagram




Figure 3: Duty Cycle parameters.

Setting the Oscillator

The times T_c and T_d can be determined as follows:

$$t_c = R_T C_T \ln\left(\frac{V_{REF} - V_{lower}}{V_{REF} - V_{upper}}\right)$$

$$t_d = R_T C_T \ln\left(\frac{V_{REF} - I_d R_T - V_{lower}}{V_{REF} - I_d R_T - V_{upper}}\right)$$

Substituting in typical values for the parameters in the above formulas:

$V_{REF} = 5.0V$, $V_{upper} = 2.7V$, $V_{lower} = 1.0V$, $I_d = 8.3mA$, then

$$t_c \approx 0.5534 R_T C_T$$

$$t_d = R_T C_T \ln\left(\frac{2.3 - 0.0083\ R_T}{4.0 - 0.0083\ R_T}\right)$$

For better accuracy R_T should be ≥10kΩ.

Grounding

High peak currents associated with capacitive loads necessitate careful grounding techniques. Timing and bypass capacitors should be connected close to Gnd in a single point ground.

The transistor and 5kΩ potentiometer are used to sample the oscillator waveform and apply an adjustable ramp to Sense.

Package Specification


PACKAGE DIMENSIONS IN mm (INCHES)

	D			
Lead Count	**Metric**		**English**	
	Max	Min	Max	Min
8L SO Narrow	5.00	4.80	.197	.189
14L SO Narrow	8.75	8.55	.344	.337

PACKAGE THERMAL DATA

Thermal Data		**8L SO Narrow**	**14L SO Narrow**	
$R_{\Theta JC}$	typ	45	30	°C/W
$R_{\Theta JA}$	typ	165	125	°C/W

Surface Mount Narrow Body (D); 150 mil wide



REF: JEDEC MS-012

Ordering Information

Part Number	**Description**
CS52845ED8	8L SO Narrow
CS52845EDR8	8L SO Narrow *(tape & reel)*
CS52845ED14	14L SO Narrow
CS52845EDR14	14L SO Narrow *(tape & reel)*

Cherry Semiconductor Corporation reserves the right to make changes to the specifications without notice. Please contact Cherry Semiconductor Corporation for the latest available information.

© 1999 Cherry Semiconductor Corporation

TradeElectronics.ru

гарантия бесперебойности производства и качества выпускаемой продукции

О компании

ООО "ТрейдЭлектроникс" - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Наличие собственной эффективной системы логистики обеспечивает надежную поставку продукции по конкурентным ценам в точно указанные сроки.

Срок поставки со стоков в **Европе и Америке – от 3 до 14 дней.**

Срок поставки из **Азии – от 10 дней.**

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Предоставляем спец цены на элементы для создания инженерных сэмплов.

Упорный труд, качественный результат дают нам право быть уверенными в себе и надежными для наших клиентов.

Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование

Наша организация особенно сильна в поставках модулей, микросхем, пассивных компонентов, ксайленсах (XC), EPF, EPM и силовой электроники.

Большой выбор предлагаемой продукции, различные виды оплаты и доставки, позволят Вам сэкономить время и получить максимум выгоды от сотрудничества с нами!

Trade Electronics.ru

гарантия бесперебойности производства и качества выпускаемой продукции

Перечень производителей, продукцию которых мы поставляем на российский рынок



Trade Electronics.ru

гарантия бесперебойности производства и качества выпускаемой продукции

С удовольствием будем прорабатывать для Вас поставки всех необходимых компонентов по текущим запросам для скорейшего выявления групп элементов, по которым сотрудничество именно с нашей компанией будет для Вас максимально выгодным!

С уважением,

Менеджер отдела продаж ООО

«Трейд Электроникс»

Шишлаков Евгений

8 (495)668-30-28 доб 169

manager28@tradeelectronics.ru

http://www.tradeelectronics.ru/