

**SPDT UltraCMOS®**  
**10 MHz – 3.0 GHz RF Switch**

## Product Description


The PE42421 UltraCMOS® RF switch is designed to cover a broad range of applications from 10 MHz through 3000 MHz. This reflective switch integrates on-board CMOS control logic with a low voltage CMOS-compatible control interface, and can be controlled using either single-pin or complementary control inputs. Using a nominal +3-volt power supply voltage, a typical input 1 dB compression point of +33.5 dBm can be achieved.

The PE42421 SPDT RF switch is manufactured on Peregrine's UltraCMOS® process, a patented variation of silicon-on-insulator (SOI) technology on a sapphire substrate, offering the performance of GaAs with the economy and integration of conventional CMOS.

## Features

- Single-pin or complementary CMOS logic control inputs
- Low insertion loss: 0.35 dB at 1000 MHz, 0.5 dB at 2000 MHz
- Isolation of 30 dB at 1000 MHz, 20 dB at 2000 MHz
- Typical input 1 dB compression point of +33.5 dBm
- 1.8V minimum power supply voltage
- SC-70 package

**Figure 1. Functional Diagram**



**Figure 2. Package**

6-lead SC-70




**Table 1. Electrical Specifications @ +25°C,  $V_{DD} = 3V$  ( $Z_S = Z_L = 50\Omega$ )**

| Parameter                        | Condition                                                                                        | Minimum                    | Typical                    | Maximum      | Unit             |
|----------------------------------|--------------------------------------------------------------------------------------------------|----------------------------|----------------------------|--------------|------------------|
| Operation Frequency <sup>1</sup> |                                                                                                  | 10 MHz                     |                            | 3000         | MHz              |
| Insertion Loss <sup>3</sup>      | 1000 MHz<br>2000 MHz                                                                             |                            | 0.35<br>0.50               | 0.45<br>0.60 | dB<br>dB         |
| Isolation                        | 1000 MHz<br>2000 MHz                                                                             | 29<br>19                   | 30<br>20                   |              | dB<br>dB         |
| Return Loss <sup>3</sup>         | 1000 MHz<br>2000 MHz                                                                             | 21<br>24                   | 22<br>27                   |              | dB<br>dB         |
| 'ON' Switching Time              | 50% CTRL to 0.1 dB of final value, 1 GHz                                                         |                            | 1.50                       |              | us               |
| 'OFF' Switching Time             | 50% CTRL to 25 dB isolation, 1 GHz                                                               |                            | 1.50                       |              | us               |
| Video Feedthrough <sup>2</sup>   |                                                                                                  |                            | 15                         |              | mV <sub>pp</sub> |
| Input 1 dB Compression           | 1000 MHz @ 2.3 - 3.3V<br>1000 MHz @ 1.8 - 2.3V<br>2500 MHz @ 2.3 - 3.3V<br>2500 MHz @ 1.8 - 2.3V | 31.5<br>29.5<br>28.5<br>28 | 33.5<br>30.5<br>30.5<br>29 |              | dBm              |
| Input IP3                        | 1000 MHz, 20dBm input power                                                                      |                            | 55                         |              | dBm              |

- Notes: 1. Device linearity will begin to degrade below 10 MHz  
2. The DC transient at the output of any port of the switch when the control voltage is switched from Low to High or High to Low in a 50 $\Omega$  test set-up, measured with 1ns risetime pulses and 500 MHz bandwidth  
3. A tuning capacitor must be added to the application board to optimize the insertion loss and return loss performance. See *Figure 6* for details

**Figure 3. Pin Configuration (Top View)**



**Table 2. Pin Descriptions**

| Pin No. | Pin Name                | Description                                                                                                                                                                                                                                                                                    |
|---------|-------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1       | RF1 <sup>4</sup>        | RF Port1                                                                                                                                                                                                                                                                                       |
| 2       | GND                     | Ground connection. Traces should be physically short and connected to ground plane for best performance.                                                                                                                                                                                       |
| 3       | RF2 <sup>4</sup>        | RF Port2                                                                                                                                                                                                                                                                                       |
| 4       | CTRL                    | Switch control input, CMOS logic level.                                                                                                                                                                                                                                                        |
| 5       | RFC <sup>4</sup>        | RF Common                                                                                                                                                                                                                                                                                      |
| 6       | CTRL or V <sub>DD</sub> | This pin supports two interface options:<br><i>Single-pin control mode.</i> A nominal 3-volt supply connection is required.<br><i>Complementary-pin control mode.</i> A complementary CMOS control signal to CTRL is supplied to this pin. Bypassing on this pin is not required in this mode. |

Note: 4. All RF pins must be DC blocked with an external series capacitor or held at 0 V<sub>DC</sub>

**Table 3. Operating Ranges**

| Parameter                                                                           | Min                  | Typ | Max                  | Unit |
|-------------------------------------------------------------------------------------|----------------------|-----|----------------------|------|
| V <sub>DD</sub> Power Supply Voltage                                                | 1.8                  | 3.0 | 3.3                  | V    |
| I <sub>DD</sub> Power Supply Current (V <sub>DD</sub> = 3V, V <sub>CTRL</sub> = 3V) |                      | 9   | 20                   | μA   |
| Control Voltage High                                                                | 0.7x V <sub>DD</sub> |     |                      | V    |
| Control Voltage Low                                                                 |                      |     | 0.3x V <sub>DD</sub> | V    |

## Moisture Sensitivity Level

The Moisture Sensitivity Level rating for the PE42421 in the SC70 package is MSL1.

## Switching Frequency

The PE42421 has a maximum 25 kHz switching rate.


**Table 4. Absolute Maximum Ratings**

| Symbol           | Parameter/Condition                         | Min  | Max                  | Unit |
|------------------|---------------------------------------------|------|----------------------|------|
| V <sub>DD</sub>  | Power supply voltage                        | -0.3 | 4.0                  | V    |
| V <sub>I</sub>   | Voltage on any DC input                     | -0.3 | V <sub>DD</sub> +0.3 | V    |
| T <sub>ST</sub>  | Storage temperature range                   | -65  | 150                  | °C   |
| T <sub>OP</sub>  | Operating temperature range                 | -40  | 85                   | °C   |
| P <sub>IN</sub>  | Input power (50 Ω)                          |      | +34 <sup>5</sup>     | dBm  |
| V <sub>ESD</sub> | ESD Voltage (HBM, ML_STD 883 Method 3015.7) |      | 2000                 | V    |
|                  | ESD Voltage (MM, JEDEC, JESD22-A114-B)      |      | 100                  | V    |

Notes: 5. To maintain optimum device performance, do not exceed Max P<sub>IN</sub> at desired operating frequency (see Figure 4)

Exceeding absolute maximum ratings may cause permanent damage. Operation should be restricted to the limits in the Operating Ranges table. Operation between operating range maximum and absolute maximum for extended periods may reduce reliability.

**Figure 4. Maximum Input Power**



## Latch-Up Avoidance

Unlike conventional CMOS devices, UltraCMOS® devices are immune to latch-up.

## Electrostatic Discharge (ESD) Precautions

When handling this UltraCMOS® device, observe the same precautions that you would use with other ESD-sensitive devices. Although this device contains circuitry to protect it from damage due to ESD, precautions should be taken to avoid exceeding the specified rating.

**Table 5. Single-pin Control Logic Truth Table**

| Control Voltages                                     | Signal Path |
|------------------------------------------------------|-------------|
| Pin 6 ( $V_{DD}$ ) = $V_{DD}$<br>Pin 4 (CTRL) = High | RFC to RF2  |
| Pin 6 ( $V_{DD}$ ) = $V_{DD}$<br>Pin 4 (CTRL) = Low  | RFC to RF1  |

**Table 6. Complementary-pin Control Logic Truth Table**

| Control Voltages                                                     | Signal Path |
|----------------------------------------------------------------------|-------------|
| Pin 6 ( $\overline{CTRL}$ or $V_{DD}$ ) = Low<br>Pin 4 (CTRL) = High | RFC to RF2  |
| Pin 6 ( $\overline{CTRL}$ or $V_{DD}$ ) = High<br>Pin 4 (CTRL) = Low | RFC to RF1  |

## Control Logic Input

The PE42421 is a versatile RF CMOS switch that supports two operating control modes; single-pin control mode and complementary-pin control mode.

*Single-pin control mode* enables the switch to operate with a single control pin (pin 4) supporting a +3-volt CMOS logic input, and requires a dedicated +3-volt power supply connection on pin 6 ( $V_{DD}$ ). This mode of operation reduces the number of control lines required and simplifies the switch control interface typically derived from a CMOS  $\mu$ Processor I/O port.

*Complementary-pin control mode* allows the switch to operate using complementary control pins CTRL and  $\overline{CTRL}$  (pins 4 & 6), that can be directly driven by +3-volt CMOS logic or a suitable  $\mu$ Processor I/O port. This enables the PE42421 to be used as a potential alternate source for SPDT RF switch products used in positive control voltage mode and operating within the PE42421 operating limits.

## Evaluation Kit


The SPDT switch EK Board was designed to ease customer evaluation of Peregrine's PE42421. The RF common port is connected through a 50 $\Omega$  transmission line via the top SMA connector, J1. RF1 and RF2 are connected through 50 $\Omega$  transmission lines via SMA connectors J2 and J3, respectively. A through 50 $\Omega$  transmission is available via SMA connectors J4 and J5. This transmission line can be used to estimate the loss of the PCB over the environmental conditions being evaluated.

The board is constructed of a two metal layer FR4 material with a total thickness of 0.031". The bottom layer provides ground for the RF transmission lines. The transmission lines were designed using a coplanar waveguide with ground plane model using a trace width of 0.0476", trace gaps of 0.030", dielectric thickness of 0.028", metal thickness of 0.0021" and  $\epsilon_r$  of 4.4.

J6 and J7 provide a means for controlling DC and digital inputs to the device. J6-1 is connected to the device  $V_{DD}$  or CTRL input. J7-1 is connected to the device CTRL input.


**Figure 5. Evaluation Board Layouts**

Peregrine Specification 101-0162-02



**Figure 6. Evaluation Board Schematic**

Peregrine Specification 102-0756-01



Typical Performance Data @ -40°C to 85°C (Unless Otherwise Noted)

Figure 7. Insertion Loss




Figure 8. Isolation – Input to Output




Figure 9. Isolation – Output to Output





Figure 10. Return Loss (Input)



Typical Performance Data @  $V_{DD} = 2.3V$ ,  $T = 25^{\circ}C$

Figure 11. Insertion Loss




Figure 12. Isolation – Input to Output




Figure 13. Isolation – Output to Output






Figure 14. Return Loss (Input & Output)




**Figure 15. Package Drawing**

6-lead SC-70



181-0013

**Figure 16. Top Marking Specification**



17-0021



[illegible]

1. 10 sprocket hole pitch cumulative tolerance  $\pm 0.02$ .
2. Camber not to exceed 1mm in 100mm.
3. Material: Black Conductive Advantek Polystyrene.
4. Ao and Bo measured on a plane 0.3mm above the bottom of the pocket
5. Ko measured from a plane on the inside bottom of the pocket to the top surface of the carrier.
6. Pocket position relative to sprocket hole measured as true position of pocket, not pocket hole.

Diagram illustrating the top view of a device. The device is shown as a rectangular block with a central square area labeled "Top of Device". The diagram includes a top view and a side view, with a label "Top of Device" pointing to the central square area in both views.

### Device Orientation in Tape

| Order Code    | Part Marking | Description            | Package            | Shipping Method  |
|---------------|--------------|------------------------|--------------------|------------------|
| EK42421-01    | PE42421-EK   | PE42421 Evaluation Kit | Evaluation Kit     | 1 / Box          |
| PE42421SCAA-Z | 421          | PE42421 SPDT RF Switch | Green 6-lead SC-70 | 3000 units / T&R |

For sales and contact information please visit [www.psemi.com](http://www.psemi.com).

No patent rights or licenses to any circuits described in this datasheet are implied or granted to any third party. Peregrine's products are not designed or intended for use in devices or systems intended for surgical implant, or in other applications intended to support or sustain life, or in any application in which the failure of the Peregrine product could create a situation in which personal injury or death might occur. Peregrine assumes no liability for damages, including consequential or incidental damages, arising out of the use of its products in such applications.

The Peregrine name, logo, UltraCMOS and UTSi are registered trademarks and HaRP, MultiSwitch and DuNE are trademarks of Peregrine Semiconductor Corp.



## О компании

ООО "ТрейдЭлектроникс" - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Наличие собственной эффективной системы логистики обеспечивает надежную поставку продукции по конкурентным ценам в точно указанные сроки.

Срок поставки со стоков в **Европе и Америке – от 3 до 14 дней.**

Срок поставки из **Азии – от 10 дней.**

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Предоставляем спец цены на элементы для создания инженерных сэмплов.

**Упорный труд, качественный результат дают нам право быть уверенными в себе и надежными для наших клиентов.**



### Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование

Наша организация особенно сильна в поставках модулей, микросхем, пассивных компонентов, ксайленсах (XC), EPF, EPM и силовой электроники.

Большой выбор предлагаемой продукции, различные виды оплаты и доставки, позволят Вам сэкономить время и получить максимум выгоды от сотрудничества с нами!

## Перечень производителей, продукцию которых мы поставляем на российский рынок





Trade Electronics.ru

гарантия бесперебойности производства и  
качества выпускаемой продукции

С удовольствием будем прорабатывать для Вас поставки всех необходимых компонентов по текущим запросам для скорейшего выявления групп элементов, по которым сотрудничество именно с нашей компанией будет для Вас максимально выгодным!

С уважением,

Менеджер отдела продаж ООО

«Трейд Электроникс»

Шишлаков Евгений

8 (495)668-30-28 доб 169

manager28@tradeelectronics.ru

<http://www.tradeelectronics.ru/>